

## Model **SA-20** 20 KVA

All SA-20 “**D Class**” systems are fully instrumented vibration amplifiers. They provide field power, cooling power and protection interlocks in addition to high quality power amplification.

**SA-20, 20 KVA** amplifiers use a full complement of power modules and a field supply for operating the Dynamic Solutions shakers at full force, with power to spare.

### **Other Shakers**

These systems are designed with the ability to be readily adapted to other shakers from other manufacturers. Consult our factory for your custom application needs.



---

# **Model SA-20**

## **D Class 20 KVA**

### **Vibration Amplifier Performance**

September 2002

#### **General**

This specification describes a SA-20 which is a complete power amplification system including armature power amplification, field power supply, full instrumentation and all necessary safety interlocks for equipment and personnel protection. Amplifier is manufactured and tested in accordance with ISO 9001.

#### **1.1 D Class Logic Module**

The control module houses the system modulator, (converts the analog input signal to an equal digital pulse string) current limiting, interlock circuitry and system alarms.

#### **1.2 Output Matching Transformer**

Space is provided for an output-matching transformer if needed, not installed in this system.

#### **1.3 Main Frame**

All of the above are housed in an attractive main frame, which also provides the AC & DC power distribution as well as vacant space for optional features.

## 2.0 INPUT CHARACTERISTICS

**2.1 Input Voltage:** A universal input transformer allows a system to be quickly connected for any of the popular forms. Specify form when ordering.

- A. 220/380 VAC, 3 phase, 5 wire WYE.
- B. 230/400 VAC, 3 phase, 5 wire WYE.
- C. 240/416 VAC, 3 phase, 5 wire WYE.
- D. 460 VAC, 3 phase, 4 wire Delta.
- E. 277/480 VAC, 3 phase, 5 wire WYE.

**2.2 Input Voltage Range:** +/- 10% of nominal.

**2.3 Input Frequency:** 47 to 63 Hz.

**2.4 Input Disturbance Tolerance:** System will deliver full power for 10 milliseconds when subjected to loss of input power

## 3.0 BLOWER POWER

**3.1 Form:** Matches input form selected.

**3.2 Protection:** Fuses and contactor for required horsepower, max. blower motor.

## 4.0 OUTPUT

**4.1 Output Power:** 20 KVA

**4.2 Output Voltage:** 0 to 120 VAC RMS, 0-170 VAC peak.

**4.3 Line Regulation/Stability:** Less than 0.05% for a 10% input voltage change.

**4.4 RMS Output Current:** 200 amps

**4.5 Peak Output Current:** 600 amps peak

**4.6 Overload:** 260% for 10 seconds, short circuit 0.5 seconds. Trip time is proportional to overload and auto adjust for maximum system protection.

**4.7 Frequency Range:** Full power, 2 Hz to 3500 Hz.

**4.8 Signal To Noise Ratio:** Greater than 70 dB below full output with input shorted.

**4.9 Total Harmonic Distortion:** <1% measured with a resistive load at 100% of rated power

**4.10 Input Sensitivity:** 1.5 Vrms for full output of 120 Vrms.

**4.11 Input Impedance:** 10 K ohms for direct coupled

**4.12 Switching Rate Frequency:** 120 Khz

## 5.0 FIELD SUPPLY

**5.1 Voltage:** Defined by Shaker requirements.

**5.2 Current:** Defined by Shaker requirements

**5.3 Protection:** Fuses

## **6.0 INTERLOCKS & SAFETY CIRCUITS**

### **6.1 Automatic Amplifier Protection Interlocks:**

- A. Input over /under voltage
- B. Shaker over-temp
- C. Shaker over-travel
- D. Logic fault.
- E. Output over voltage and current

## **7.0 ENVIRONMENTAL / MECHANICAL**

**7.1 Cooling:** Internal cooling fans

**7.2 Heat Loading:** 2 KW at full load, proportionally reduced at lighter loads.

**7.3 Temperature Range:** 0 to 40 degrees C.

**7.4 Humidity:** 0 to 95%, non condensing.

**7.5 EMI/RFI:** Per FCC part 15J, Class A for both conducted and radiated.

**7.6 Dimensions:** 550×1700×800 mm      21.65 x 66.9 x 31.49 in

**7.7 Weight:** 1000 lbs.

**Sales Office**  
**P.O. Box 7963**  
**Northridge, CA 91327**  
**Ph. 818.831.0832 Fx. 818.831.0842**  
[www.dynsolusa.com](http://www.dynsolusa.com)